

Multi-Band Fender Mount Antenna Systems

Covert Direct Replacement Fender Mount

Available In VHF/UHF, VHF/7-800 & VHF/UHF/7-800

- OEM hardware for simple installation
- Designed specifically for the make model and year of each vehicle
- Available for multi-port radios & all-band single-port radios
- Allows simultaneous operation of AM/FM radio

MODEL NUMBER*	DB-VHF/UHF		DB-VHF/7-800		DB-VHF/7-800-SP		TB-VHF/UHF/7-800-SP		
Frequency Range (MHz)	150-174/406-512*		150-174* / 760-870		136-174* / 760-870		136-174* / 406-512* / 760-870		
Bandwidth (Mhz)	24	34*	24*	110	24*	110	24*	24*	110
Power Rating(watts)	150		150	35	150		150		
Finish	OEM Match								
Maximum Height (inches)	28-36 MAX								
Mounting Hardware	OEM Hardware								
Mast Material	Stainless Steel or Fiberglass								
Feed Line	17" RG58					RG303			
Connector	PL259, Mini UHF, BNC, TNC, SMA, N Type, QMA								

When Ordering: Please provide the year, make , model and trim of your vehicle.

* Specify operating frequency(s). Some vehicle models may be split band VHF or UHF

SP models are specific for single port all-band radios

