

Exclusive Flexi-Whip Magnetic Mount Antenna

Proven Durability Reduces Vehicle Downtime

- Doesn't break on impact. Bends and bounces back
- \cdot Field tunable from 136MHz to 1Ghz
- · Significantly reduces life cycle cost on fleet vehicles
- Retrofit existing NMO mounts
- \cdot Available in NMO roof-mount and magnet mount

MODEL NUMBER		MGNT-FT-NITI	
Frequency Range(MHz)		136MHZ - 1GHz	
Bandwidth (MHz)	18 Mhz @ 136	90 MHz @ 450	150 @ 850
SWR		<2:1	
Power Rating (watts)	150		
Gain	Unity		
Pattern	Omni-directional		
Mast Material	Rubber coated Nitinol		
Maximum Height	23" @ 136MHz		
Feed Line	17 ft. RG-58/U		
Connectors (choose one)	PL259, Mini UHF, BNC, TNC, SMA, N, QMA		



*MGNT-FT-NITI(Magnet Mount)

Also available in: ROOF-FT-NITI(Roof Mount)

